

MATV and Home Distribution Amplifiers




CATV

Integrated attenuator
and slope control



Forward gain switchable



Optional:

Universal AC Adapter

SNG 18/1000 (Art. No.: 832114)

in combination with Line Power Injection Filter
FSW 30 F (Art. No.: 815018).



HNV 30 UPE, HNF 30 URP

- For MATV and CATV systems.
- Remote powering on input and output side (only HNF 30 URP).

Miscellaneous:

- The devices are equipped with a switched-mode power supply.

Tech hint HNF 30 URP

The remote power is available on the input and output side. This has the advantage that another remote powered amplifier can be supplied with voltage. On ports where it is not desired, a **DCF 500 (set of 2 pcs. Art.No.: 871506)** must be used.

Model Art. No.	HNV 30 UPE 811269	HNF 30 URP 811304
EAN	4040326112694	4040326113042
Inputs/outputs	1 / 1	1 / 1
Gain 47 ... 862 MHz	30 or 20 dB	30 or 20 dB
Output level max. 60 dB IMA ₃ /EN 60728-3	108 dBμV	108 dBμV
Level adjusting range	0 ... -12 dB	0 ... -12 dB
Slope correction range	0 ... -15 dB	0 ... -15 dB
Mains power supply U~	100 - 240V/47 - 63 Hz	15 ... 20V/210 mA
Power consumption	max. 5 W	-
Ambient temperature	-20 ... +50 °C	-20 ... +50 °C
Dimensions (mm)	194 x 86 x 52	138 x 83 x 52